



Ranger SRA-166FB

Frequency Counter & External Speaker



Technical Specifications

Speaker

Nominal Size : 78 mm. 3 Inch

Voice Coil Imp : $4 \pm 15\%$ At 1000 Hz. 1 V.

Resonant Fo : 90 Hz. ± 18 Hz.

S.P.L. : 96 dB/W ± 3 dB 1 W 50 cm

Responce FO Hz : -10KHz 20dB Max 500,600,800,1000 Hz

Input Nominal Power : 12 W

Maximum Power : 15 W

Magnet Size : 60*32*10 mm

Distortion : 5% max.

Plug Type : 3.5mm

Wire Length : 2 meter

Accessories : Mounting Bracket and Screw

Frequency Counter Display

Frequency Range : 1 MHz ~ 40

Power Requirements : 8 – 13.8

Display counter : Blue light

Dimmer Control : Manually to adjust the brightness.

Current Consumption : 60 mA

Input Impedance : 5K Ohm,

Standard Oscillating Frequency : 4.5 MHz, ± 10 ppm

Ranger Communications Inc.
867 Bowsprit Road,
Chula Vista CA 91914

(619)-271-4035

Email : sales@rangerusa.com